



C-1000-4

4 ZONLU KONVANSİYONEL YANGIN ALARM PANELİ
4 Zone Conventional Fire Alarm Panel

C-1000-8

8 ZONLU KONVANSİYONEL YANGIN ALARM PANELİ
8 Zone Conventional Fire Alarm Panel

C-1000-16

16 ZONLU KONVANSİYONEL YANGIN ALARM PANELİ
16 Zone Conventional Fire Alarm Panel



C-1000-4R (Repeater)

4 ZONLU KONVANSİYONEL TEKRARLAMA PANELİ
4 Zone Conventional Repeater Panel

C-1000-8R (Repeater)

8 ZONLU KONVANSİYONEL TEKRARLAMA PANELİ
8 Zone Conventional Repeater Panel

C-1000-16R (Repeater)

16 ZONLU KONVANSİYONEL TEKRARLAMA PANELİ
16 Zone Conventional Repeater Panel

KONVANSİYONEL YANGIN ALARM PANELİ

Conventional Fire Alarm Panel

TANIM: C-1000-4-08-16 Konvansiyonel Yangın Panelleri 4 bölge 8 Bölge 16 Bölge smd Devre Kart uygulaması ile tasarlanmış ve geliştirilmiştir. Sistemde yangın ya da arıza bilgisi panel üzerinde bölge (zone) bazında görülür. Sistemin kurulu bulunduğu bina bölümlere ayrılmıştır. Bu bölümlere kat bazında yada bina bazında yapılabilir. Sistemde kablo tesisatı, oluşturulacak bölge sayısına göre yapılır. Her bölgeye en fazla 20 detektör bağlanabilmektedir. istenildiği kadar yangın ihbar butonu kullanılabilir. Siren kablosu panelden ayrı olarak çekilir. Sistemde kablo çekimi, bölgelerin oluşturulması, sistemde kullanılacak elemanların yerleşimi aşağıdaki diyagramda görüldüğü gibi yapılır. Küçük ölçekli uygulamalar için ekonomik çözümler sunan, modern bir dış görünüme sahip ve yüzey montaj teknoijisi üretim tekniği ile üretilen konvansiyonel sistem yangın alarm santralleridir.

DEFINITION: C-1000-4-08-16 Conventional Fire Panels are designed and developed with 4-zone 8-zone 16-zone smd Circuit Board application. Fire or fault information in the system is displayed on the panel on a regional basis. The building where the system is installed is divided into sections. This partition can be made on the basis of floors or buildings. The cable installation in the system is made according to the number of zones to be created. Up to 20 detectors can be connected to each zone. Fire alarm buttons can be used as many times as desired. Sounder cable is pulled separately from the panel. Cable pulling in the system, creation of zones, placement of the elements to be used in the system are done as shown in the diagram below.

They are conventional system fire alarm control panels that offer economical solutions for small-scale applications, have a modern appearance and are produced with surface mounting technology production technique.



TEKNİK VE TEMEL ÖZELLİKLER:

- EN54-2-4 Standartlarında Tasarım ve Test
- Membran Panelli
- Her Zone için Alarm ve Hata Ledi
- 24V Akü Kapasiteli
- Alarm ve Hata Röle Çıkışları
- Harici 24Vdc Besleme Çıkışı
- Güvenli ve Hızlı Haberleşme
- Topraklama Hatası Algılama
- Şebeke ve Akü Hata Uyarıları
- Tahliye Anahtarı
- Tuş Takımı Kilidi
- Zonları Devre Dışı Bırakabilme
- Tek Kişi ile Test Yapabilme
- Tüm Konvansiyonel algılama ve uyarı Cihazları ile uyumlu
- Tekrarlama Panel Bağlantısı
- Bölgeleri Teste Alabilme
- Gece Gündüz Modu
- Tüm Hata Kodlarını Denetleyebilme
- Tahliye Butonu ile Sirenleri aktive edebilme
- Yüzeye Montaj
- Sessiz Butonu ile Sirenleri Susturabilme
- Algılama Zone Sayısı 4,8, 16
- 1 Bölgeye bağlanabilecek duman.ısı Alev Dedektörü 20 Adet
- 1 Bölgeye Bağlanabilecek Gaz ve Beam Dedektörü Sınırsız
- 1 Bölgeye Bağlanabilecek Buton Sayısı Sınırsız
- Panel Beslemesi: 220 (+ - 10%) VAC 50/60 Hz
- Çalışma Gerilimi: 24 VDC
- Çalışma Sıcaklığı: -10 oC +55 oC (%95 Nem)
- Koruma Sınıfı: iP 30
- Uygulama Alanı: Bina içi kullanımı
- Akü:2 Adet 12VDC 4Amph.
- Akü Şarj Akımı:0.5 MA

TECNICAL AND BASIC FEATURES:

- Design and Test in EN54-2-4 Standards
- With Membrane Panel
- Alarm and Error LED for Each Zone
- 24V Battery Capacity
- Alarm and Fault Relay Outputs
- External 24Vdc Supply Output
- Safe and Fast Communication
- Ground Fault Detection
- Mains and Battery Error Alerts
- Evacuation Switch
- Keypad Lock
- Ability to Disable Suspects
- Testing with a Single Person
- Compatible with all Conventional detection and warning devices
- Repeat Panel Connection
- Ability to Test the Regions
- Day and Night Mode
- Ability to Check All Error Codes
- Ability to activate the Sirens with the Evacuation Button
- Surface Mounting
- Silencing the Sirens with the Silent Button
- Detection Zone Number 4,8, 16
- Smoke Heat Flame Detector that can be connected to 1 Zone 20 Pieces
- Gas and Beam Detectors that can be connected to 1 Zone Unlimited
- The Number of Buttons That Can Be Connected to 1 Zone is Unlimited
- Panel Feed: 220 (+ - 10%) VAC 50/60 Hz
- Operating Voltage: 24 VDC
- Working Temperature: -10°C to +50°C (95% Humidity)
- Protection Class: iP 30
- Application Area: Indoor use
- Battery: 2 pieces 12VDC 4Amph.
- Battery Charge Current: 0.5 MA

